

# EDC-KBD1

Home | Security | Recording | Accessories

EDC-KBD1  
System Keyboard with 3-axis Joystick, 12VDC,

Art-Nr. 74088



## Main Features

**Programming and control of camera series:**  
Fastrax and Minitrax  
For DVR series DLR1.2, DLR3/4, DTR, DIR and DPR  
Supports up to 254 cameras  
Joystick control of PTZ functions

**Programmable sequences and patterns**  
**Preset position and pattern control**  
**Auto and random scanning**  
**Auxiliary operation**

## Specifications

<b>Integrated monitor</b>	-
<b>Weight</b>	approx. 1.2kg
<b>Video input</b>	-
<b>Supply voltage</b>	12VDC (connection to the Junction box, 230VAC PSU included)
<b>Site control (direct mode operation)</b>	Keys select cameras and monitors, operates up to 254 presets, 4 patterns, 8 scans. Capability to incorporate up to 300 of presets, patterns, scan and tour itself in up to 8 tours. Camera functions: pan, tilt, zoom, focus, iris for fixed or variable speed control of the camera series Fastrax, Minitrax. Auxiliaries and sequences.
<b>Baud rate</b>	2.400 ~230.000
<b>Interface</b>	3x RS-485, RJ45 (8-pin). 1x KBD (For connection of the junction box: Dome camera series Fastrax), 1x DVR (Recorder series DLR, DTR, DPR)
<b>Remote control</b>	Control of up to 254 Fastrax and/or Minitrax dome cameras, camera series Almira. Up to 99 Digital Video recorders of the series DLR and DTR

# EDC-KBD1

(Continuation Spezifications)

<b>LCD display</b>	16x2 characters
<b>Power consumption</b>	Approx. 5 watts
<b>Temperature range</b>	0 ~+50°C
<b>Dimensions (HxWxD)</b>	96 (incl. Joystick) x380x168mm
<b>Parts supplied</b>	System keyboard, Junction box with connection cable and PSU
<b>Certificates</b>	CE

SLD Security & Communications  
The Old Forge, Ockham Lane, Ockham, Surrey GU236PH England  
Phone +44.1483225633 · Fax +44.1483225634  
sales@sld.co.uk · www.sld.co.uk

